

INDIANA JONES OPERATIONS MANUAL AMENDMENT for manual 16-50017-101

This amendment reflects changes that occurred after the INDIANA JONES Operations Manual was printed. Please keep this amendment with your manual.

Page 1-35: A.2 35 Jackpot Difficulty

The operator selects how hard it is to collect jackpot and multiply jackpots during 3 ball idol multiball.

Settings: EASY - Center drop target bank does not reset when starting multiball or when a ball enters the center idol lock hole for a jackpot multiplier.
 HARD - Center drop target bank resets at the start of the multiball and each time a ball enters the center idol lock hole. Also, once a jackpot has been collected the center drop targets will automatically reset every few seconds.

Page 2-15: 3-bank Drop Target Opto PCB Assembly

The part number for LED 1 was 5671-09019-00. It has been changed to 5671-13732-00.

Page 2-15, 2-44 and 3-20: 3-sw. Opto PCB Assembly

The part number for the 3-sw. Opto PCB Assembly was A-13901-2. It has been changed to A-17042-3. On page 3-20, R10 is shown as 220KΩ. It should be 22KΩ.

Page 2-22: Ball Trough Assembly

The wire colors have been changed as follows:

Gray-Green becomes Gray-Violet

Gray-Violet becomes Gray-Green

Orange-Violet becomes Orange-Green

Orange-Green becomes Orange-Violet

Page 3-20 and 3-21: 3-sw. Opto PCB Assembly

On connector J1-7, the Violet-White wire for switch column 9 should come from the 8-driver board connector J5-1 not J5-4.

Page 3-22: 8-driver PCB Assembly

The Violet-White wire for switch column 9 going to the Motor Opto PCB and the 3-sw Opto PCB comes from J5-1 not J5-4.

Page 3-24: Motor Opto Switch PCB Assembly

On connector J1-6, the Violet-White wire for switch column 9 should come from the 8-driver board connector J5-1 not J5-4.